



## Main

Range	Masterpact
Device short name	XF diag & com
Product or component type	Voltage release
Device application	Control
Range compatibility	Masterpact MTZ2 circuit-breaker Masterpact MTZ3 circuit-breaker
Voltage release type	Closing coil

## Complementary

Control type	Communicating
Signalling function	Electrical push-button activated Error Ready to close or open Coil powered
[Un] voltage power supply	48 V AC 50/60 Hz 48...60 V DC
Threshold tripping voltage	0.85...1.1 Un on closing
Holding power consumption	4.5 W
Circuit breaker mounting mode	Drawout
Maximum response time	80 ms on closing for Masterpact MTZ2 90 ms on closing for Masterpact MTZ3

## Offer Sustainability

Sustainable offer status	Green Premium product
REACH Regulation	<a href="#">REACH Declaration</a>
EU RoHS Directive	Compliant <a href="#">EU RoHS Declaration</a>
Mercury free	Yes
RoHS exemption information	<a href="#">Yes</a>
China RoHS Regulation	<a href="#">China RoHS Declaration</a>
Environmental Disclosure	<a href="#">Product Environmental Profile</a>
Circularity Profile	<a href="#">End Of Life Information</a>

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.