

KRB0120YC205T

Copper flexible link, Canalis KR, connection accessory, tinned copper link, made to measure length, cross section 600mm²



Main

| | |
|------------------------------------|----------------------|
| Range | Canalis |
| Product name | KR |
| Product or component type | Flexible link |
| Device short name | KRB |
| Range compatibility | Canalis KR |
| Accessory / separate part category | Connection accessory |
| Material | Tinned copper |
| Length | 310...500 mm |

Complementary

| | |
|-----------------------|---------------------|
| Bolt diameter | M12 |
| Mounting mode | Bolt-on |
| Thickness | 5 mm |
| Nominal cross section | 600 mm ² |
| Width | 120 mm |
| Net weight | 2.7 kg |
| Quantity per set | Set of 1 |

Packing Units

| | |
|------------------------------|---------|
| Unit Type of Package 1 | PCE |
| Number of Units in Package 1 | 1 |
| Package 1 Height | 5.0 cm |
| Package 1 Width | 12.0 cm |
| Package 1 Length | 50.0 cm |
| Package 1 Weight | 2.84 kg |

Offer Sustainability

| | |
|----------------------------|---|
| Sustainable offer status | Green Premium product |
| REACH Regulation | REACH Declaration |
| REACH free of SVHC | Yes |
| EU RoHS Directive | Compliant EU RoHS Declaration |
| Mercury free | Yes |
| China RoHS Regulation | China RoHS Declaration |
| RoHS exemption information | Yes |
| Environmental Disclosure | Product Environmental Profile |
| Circularity Profile | End Of Life Information |
| WEEE | The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.