



### Main

Range	Masterpact
Product or component type	Sensor plug
Accessory / separate part category	Control unit accessory
Range compatibility	Masterpact MTZ2 Masterpact MTZ2 32 circuit breaker Masterpact MTZ3 Masterpact MTZ3 40 circuit breaker Masterpact MTZ3 Masterpact MTZ3 50 circuit breaker Masterpact MTZ3 Masterpact MTZ3 63 circuit breaker

### Complementary

[In] rated current	3200 A
--------------------	--------

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Weight	8 g
Package 1 Height	3 cm
Package 1 width	3.5 cm
Package 1 Length	8 cm

### Offer Sustainability

REACH Regulation	<a href="#">REACH Declaration</a>
REACH free of SVHC	Yes
EU RoHS Directive	Compliant <a href="#">EU RoHS Declaration</a>
Mercury free	Yes
RoHS exemption information	<a href="#">Yes</a>
China RoHS Regulation	<a href="#">China RoHS Declaration</a>
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.